



Technical note: Please do not use telephones connected to the same telephone socket during postage loading if possible. Unnecessary charges may be incurred when you lift and do not replace the telephone handset during the loading process, as the modem cannot terminate the charged connection.



Start TELESET




Caution! The Optimail locks after 8 attempts to confirm a false personal identification number (PIN). Your Optimail can only be released for metering and loading postage again by the after-sales service.



Enter your PIN



- Make sure the Optimail is connected to the telephone socket.
- Switch on the Optimail as usual and wait until the last set postage value appears in the display.
- Make sure the scales function is switched off. The scales symbol $\overline{\text{T}}$ must not show in the display.
- Type the 8-digit personal identification number (PIN) of your Optimail (“12345678” in the example).
- Confirm with the  key.

You are now in the TELESET mode. The amount used for the last postage loading appears in the display (\$ 100 in the example).


Enter the desired amount



Enter amount and load postage ...

- Leave the amount as it is or overwrite with a new value.



- Confirm the desired amount the  key.



The loading process now continues running automatically (establish connection, data exchange...). During the loading process, the word “Reset” and the amount being loaded will appear alternately in the display.




If you have changed the amount the word “Change” and the new preset amount will alternately appear in the display.

When the display shows the countdown on the left side:

Confirm the amount again



- To load the displayed amount, confirm with the  key within 30 seconds.

The countdown gives information on the remaining time to confirm.

...completed successfully

The postage is loaded when an acoustic signal sounds and the postage value appears in the display.

- Check the new available postage (register R1). To do this, press the  key once.

Interrupt TELESET

You can interrupt the procedure as long as the connection to the TELESET data center has not yet been established. To do so:

- Wrong entries (e.g. when entering amounts) can be deleted with the **C** key.
- You can enter a new amount and continue the procedure

or

exit the TELESET mode with the **C** key.

During connection setup

- Press the **C** key.

The Optimail aborts TELESET mode.

The display shows the postage value again.



You will find help for TELESET errors in Chapter 12.2.